

# Highly Efficient Washing of Microwell Plates Using Centrifugal Forces

Julia Stifel, PhD, Julian Riba, PhD


cytena, Freiburg, Germany

## Introduction

The **C.WASH**<sup>™</sup> plate washer is used to remove liquids from microwell plates by centrifugal forces. The ability to dispense liquids into the plates afterward enables the fully automated and reproducible washing of entire microwell plates in a high-throughput manner.

Here, we determined washing efficiencies achieved by the C.WASH for different rotational speeds in 96-well and 384-well microplate formats. Washing efficiency is measured as the ability to remove media, washing buffer or unbound compounds. Low residual volumes after the washing steps correlate with lower background signals in cell-based assays, ELISA or other immunoassays.

Post-wash and pre-wash fluorescent values of a plate filled with fluorescein solution were compared to determine washing efficiencies. One wash cycle is defined as the removal of liquid in the plate by centrifugal spinning, followed by liquid dispensing. Both steps can be performed using the C.WASH.



**Figure 1.** Workflow for measuring the washing efficiency using the C.WASH centrifugal liquid removal and non-contact dispensing.

## Materials and methods

### Materials

- Fluorescein (100  $\mu$ M, dissolved in H<sub>2</sub>O, CAS-Number 518-47-8)
- Solid black microplates 96-well/384-well, 4titude (4ti-0263/4ti-0264; Brooks Life Sciences)

### Measuring washing efficiencies

For each rotational speed, 96 wells were filled with a 100  $\mu$ M fluorescein solution (50  $\mu$ L for 384-well/100  $\mu$ L for 96-well microplates). Plates were emptied by centrifugal spinning for 5 seconds and subsequently filled with the same volumes of water, dispensed by the C.WASH. The fluorescent signal was measured pre-washing, after one wash cycle and after two wash cycles. Washing efficiencies were calculated as the ratio of fluorescent signal post-washing/pre-washing.


### Quantification of residual volumes

Standard curves for the quantification of remaining volume were dispensed using an **I.DOT** low volume dispenser. Volumes from 10 nL to 300 nL were dispensed in triplicate. Subsequently 50  $\mu$ L/100  $\mu$ L of water

were dispensed in all wells using the C.WASH. The resulting standard curve was used to calculate the residual fluorescein values in the experiments.

### Fluorescence measurement

All fluorescence measurements were performed with a Spark Multimode Microplate Reader (Tecan), using fluorescence top-reading.




**Figure 2.** Standard curve for the quantification of residual volumes, based on fluorescent signal. Measurements were performed in triplicates.


## Results and discussion

### Washing efficiency

The washing efficiencies for different rotational speeds are shown in **Figure 3A-B**. Even at low rotational speeds (22 xg), 99.5% of the fluorescence was removed after one washing cycle. This efficiency further increases for higher rotational speeds. After a second washing cycle, 99.99% of the fluorescent signal is removed, regardless of the rotational speed. Given these washing efficiencies, using the C.WASH, plate washing protocols can be reduced to a maximum of two washing steps, allowing simplified assay designs and faster results.




**Figure 3A.** Washing efficiencies after one or two washing cycles at different rotational speeds in a 96-well plate. Values shown in the diagram are mean values, deriving from 96 data points.



**Figure 3B.** Washing efficiencies after one or two washing cycles at different rotational speeds in a 384-well plate. Values shown in the diagram are mean values, deriving from 96 data points.

### Residual volumes after liquid removal

The remaining volume after one round of spinning are shown in **Figure 4**. Measured volumes are all below 1  $\mu\text{L}$  for all tested parameters, and for 384-well plates even below 250 nL. For the highest rotational speeds, residual volumes are as low as 50 nL. These volumes are more than 10-fold smaller than in needle-based plate washers or with manual plate tapping. Such low residual volumes will lead to reduced background signals in all plate-based assays, leading to better experimental data output.



**Figure 4.** Residual volumes after spinning at different rpm in 96-well (green) and 384-well (blue) plate format. Values shown in the diagram are mean values, deriving from 96 data points.

## Conclusions

- The C.WASH achieves very high washing efficiencies after just one wash cycle (>99.5% washing efficiency).
- After two wash cycles, the C.WASH achieved almost complete removal of fluorescent signal (>99.99% washing efficiency).
- Results are highly reproducible due to automation.
- C.WASH highly reduces the number of washing cycles compared to conventional needle-based systems and therefore reduces timelines and reagent consumption.

## Contact us

U.S. phone:  
+1 833-235-5465

Email:  
[info@cytena.com](mailto:info@cytena.com)

European phone:  
+49 761 70 88 90-0

Website:  
[www.cytene.com](http://www.cytene.com)



© 2021 CELLINK AB. All rights reserved. Duplication and/or reproduction of all or any portion of this document without the express written consent of CELLINK is strictly forbidden. Nothing contained herein shall constitute any warranty, express or implied, as to the performance of any products described herein. Any and all warranties applicable to any products are set forth in the applicable terms and conditions of sale accompanying the purchase of such product. CELLINK provides no warranty and hereby disclaims any and all warranties as to the use of any third-party products or protocols described herein. The use of products described herein is subject to certain restrictions as set forth in the applicable terms and conditions of sale accompanying the purchase of such product. CELLINK may refer to the products or services offered by other companies by their brand name or company name solely for clarity and does not claim any rights to those third-party marks or names. CELLINK products may be covered by one or more patents. The use of products described herein is subject to CELLINK's terms and conditions of sale and such other terms that have been agreed to in writing between CELLINK and user. All products and services described herein are intended FOR RESEARCH USE ONLY and NOT FOR USE IN DIAGNOSTIC PROCEDURES.

The use of CELLINK products in practicing the methods set forth herein has not been validated by CELLINK, and such nonvalidated use is NOT COVERED BY CELLINK'S STANDARD WARRANTY, AND CELLINK HEREBY DISCLAIMS ANY AND ALL WARRANTIES FOR SUCH USE. Nothing in this document should be construed as altering, waiving or amending in any manner CELLINK's terms and conditions of sale for the instruments, consumables or software mentioned, including without limitation such terms and conditions relating to certain use restrictions, limited license, warranty and limitation of liability, and nothing in this document shall be deemed to be Documentation, as that term is set forth in such terms and conditions of sale. Nothing in this document shall be construed as any representation by CELLINK that it currently or will at any time in the future offer or in any way support any application set forth herein.